














Print Kit

Apple Reference Card

Important Keys

	RETURN KEY: Selects a chosen menu option.	
	OPEN APPLE KEY: Use as the command key for editing functions. If you do not have an Open Apple Key, use the Equal (=) key.	
	CURSOR MOVEMENT KEYS: Up arrow key moves the cursor up. If you do not have an up arrow key, use the Control and A keys.	
	Down arrow key moves the cursor down. If you do not have a down arrow key, use the Control and Z keys.	
	Right and left arrow keys move the cursor left and right.	
		
	EDITING KEYS: The Delete key deletes the last character typed. If you do not have a Delete key, use the Control and D keys.	
		Press the Control and R keys to remove the character the cursor is on.
	ESCAPE KEY: Returns you to the previous menu.	
		Press the Control and C keys to change text between upper and lower cases.
	Q KEY: Stops printing.	



Fonts



Avant Garde
Fine Print
Headline
Old English
Times
Xmas
Zapf

Text Styles

Bold
Italics
~~**Jazz**~~
Normal
Outline
Raised
Shadow

Text Editing Commands

Fonts		Text Styles	
Change Font	F	Bold	B
Reassign Font	G	Italics	I
		Jazz	J
		Normal	N
		Outline	O
		Raised	R
		Shadow	S

Text Size		Justification	
Increases Size	A	Left Justify	L
Decreases Size	Z	Right Justify	T
		Center Text	C

Other Commands

Help Screen	H
Mask/Unmask Text	M
Exit Text Editor	X

Computer Equipment

Apple IIc/e/GS with 128K.

One disk drive required.

A dot matrix printer listed on the Printer Setup table.

Select one of the following Printer Interface cards:

Apple Parallel Interface Card, Apricorn Parallel Card, Gampier

Apple IIc Plus, MSII Parallel

Booting Your System

- Insert the Apple Print Kit program disk in Drive 1.
 - Turn ON monitor, computer, and printer.
 - The Print Kit program self-boots.
-

Printer Setup Instructions

- Be certain you choose the correct printer from the Printer Setup table.
- Select "Interface." Choose the interface that matches the one in your computer. IIC/ImageWriter users select "IIC" interface; IIGS/ImageWriter users select "NSSC Pascal" interface.
- Select "Options." If necessary, see your printer manual for specific information about line feeds and slot number. Ignore the printer device number and the secondary address choices. They have no effect on this version of the program.
- Select "Test Printer". Use the 8-inch Figure Test. Your printer should print the corners and the left edge of an 8 x 8 box. If not, you selected the wrong printer driver.
- If your printout has broken lines, your line feeds may be set incorrectly. Or, you selected the wrong printer driver.
- Select "Save Changes" after completing the Printer Setup.
- Select "Exit Print Kit" to access the Main Menu.

Apple Printer Setup

If Your Printer Is:

Choose:

Epson LX-80, Star NX-10, Gemini 10X, Panasonic 1091	Non ESC-2 Epson/IBM
IBM 5152, Commodore MPS 1000 (IBM mode), Epson FX-80, Okidata M182a/183a, Okimate 20 (IBM mode), Radio Shack DMP 130 (IBM mode)	ESC-2 Epson/IBM
Okidata ML 192/193	OKI 19X (Microline)
Okidata ML 292 /293 (Microline P.M.)	OKI 29X (Microline)
Okidata 292/293 (IBM P.M.)*	OKI 29X (IBM)*
Okimate 20 (Apple IIe P.M. with IIe Only)	
Imagewriter, Imagewriter II	Imagewriter
Panasonic KX-P1080	KX-P1080 Panasonic
Star SG 10	SG 10 Star

* 16 pin mode and 8 pin mode (where available)
Super Serial Card configured for 9600 Baud.