



Tech Info Library

High Speed Serial Interface Card: Qume Sprint 5 (11/96)

Revised: 11/20/96
Security: Everyone

High Speed Serial Interface Card: Qume Sprint 5 (11/96)

=====

Article Created: 21 September 1984
Article Reviewed/Updated: 18 November 1996

TOPIC -----

This article details the setup necessary for the High Speed Serial card and Qume Sprint 5 printer to function together.

DISCUSSION -----

Qume Setup

Form length	11 inches
Character spacing	10 or 12
Twintellect	Standard
Auto LF	On
Parity	Mark
Duplex	Test (For normal operation set to Full)
Baud rate	1200

The two switches inside the cover should be set to "MOD" and "HI".

High Speed Serial Card

Ensure the P8A PROM is installed in location B2 on the card and the switchs are set to the following.

1	2	3	4	5	6	7
Off	Off	On	Off	On	Off	On

Enter and run this BASIC program

```
10 PR# 1
20 PRINT CHR$ (27); CHR$ (26); CHR$ (14)
```

30 PR#0

The Sprint 5 printer will do the Self-Test and print "Self-Test OK", then it will print the entire character set until the Duplex switch is set to Full.

Article Change History:

18 Nov 1996 - Reviewed for technical accuracy, revised formatting.

Copyright 1984-96, Apple Computer, Inc.

Tech Info Library Article Number:515