



Adding the Chips

- 4) **Align each leg (pin) of the chip with its socket hole.** You may have to bend the pins slightly to align them with the holes. Do this by holding the chip on edge so that one of the rows of feet are against the table's surface. Now apply downward pressure to the chip while rolling it toward the bottom of the pins. This will bend the pins uniformly.
- 5) **Press down firmly on each chip** to ensure that it is fully seated in its socket. Check closely for bent pins.
- 6) **Reinstall the card** following the installation instructions.
- 7) **Test it.**

The RamFactor memory test, included on the AW 2 Expander disk, as well as the built-in diagnostics test are described in the next appendix.